

This configuration table shows how the 460R2D circuit board should be configured. If you have specific questions please give technical support a call with the spa serial number while at the spa.

Configuration Table							
Pack	Model	Relay	Black	White	Gray	Program	Dip Switch Up
460	400'S W / BLOWER	103737 1 relay US	J37	J57	J6	(n5 = b floating remote)	A2, A3, A8, B5
	400'S W/O BLOWER	NONE		N/A			A3, A8
	ELITES W/ BLOWER	NONE	MOVE RED WIRE, W15, TO J97				A2, A3, A9, B5
	ELITES W/O BLOWER	NONE		N/A			A3, A9
	MAAX 705 & 706	103738 2 relay US	J37	J57	J36		A3, A8, B1, B3
	PowerPools	103738 2 relay US	J37	J57	J36		A3, A8, B1, B3, B5
	Vita	103737 1 relay US	J37	J57	J6		A2, A3, A6, A8, B5