

## PC BOARD SET-UP OPTIONS

### **PC Board 600-6307/600-6314 (Domestic) and 600-6308 (European)**

In April 2018 all (Domestic) spas changed to one spa pack/ circuit board 600-6314.

These replacement boards will come from the factory in Set-Up 2. You will need to change the Set-Up Option to match the spa you have.

**In the Signature Series/ATV the options are:**

- Set Up 1 One Pump Spa
- Set Up 2 Two Pump Spa
- Set Up 3 Three Pump Spa
- Set Up 4 One Pump with MicroSilk®
- Set Up 5 Two Pump with MicroSilk®

**In the e-Series™ and Vector21 and Celebrity Elite, the options are:**

- Set Up 6 One pump Spa
- Set Up 7 Two Pump Spa

**In the Vector21 with Mircosilk options are:**

- Set Up 9 One pump with Microsilks
- Set UP 10 Two pumps with Microsilks

**In the Celebrity, 2019 Domestic and International spas there is only one option:**

- Set Up 8

**To change the Signature Series/ATV: (NON-TOUCHSCREEN)**

1. Turn off power to the spa
2. Flip dip switch one on the board up (on) and turn the power back on to the spa
3. Press the Back/Set button on the topside panel to exit the Priming Mode
4. Press the Settings button
5. Scroll down using the arrows on the buttons (temp up and down) to TEST on the display on the topside
6. Press the Back/Set Button
7. Scroll down to SETUP
8. Press the Back/Set button
9. Use the arrows (temp up and down) to select the Set Up required for the spa.
10. Press the Quiet Soak button to highlight save and press the Back/Set button to save it
11. Spa will reboot automatically
12. Turn power to the spa back off

## **PC BOARD SET-UP OPTIONS**

13. Flip dip switch one back down (off) and turn power back on to the spa
14. Test all functions

### **To change the Signature Series/ATV: (TOUCHSCREEN)**

1. Turn off power to the spa
2. Flip dip switch one on the board up (on) and turn the power back on to the spa
3. Press the Settings icon and then navigate to the next screen
4. Press the Test icon
5. Press the Set Up icon
6. Change the Set Up# to the corresponding number for the spa.
7. Press the Check-Mark icon (save button) to save settings.
8. The spa will reboot automatically. A message will appear stating the spa will now restart.
9. Press the Clear icon followed by the back button in the top left hand corner.
10. Turn power to the spa back off
11. Flip dip switch one back down (off) and turn the power back on to the spa
12. Test all functions

### **To change the e-Series™, Vector21, Celebrity Elite & Celebrity:**

1. Turn off power to the spa
2. Flip dip switch one up (on) and turn power back on to the spa
3. Press the Temp button to exit Priming Mode
4. Press Temp button once
5. Press Light button once
6. Press Temp button repeatedly till you get to required set up
7. Press Light button to save
9. Spa will reboot automatically
10. Turn power off the spa
11. Flip dip switch one down (off) and turn power back on to the spa
12. Test all functions